



interM

PA-935N | 35W Mixer Amplifier


The PA935N is a 35 watt compact, desktop mixer amplifier ideal for use in smaller installations such as waiting rooms, office, factories, educational and retail applications.

Features Telephone Paging Input. Provides clear voice and full range background music.

Features:

- Compact design
- 1 Mic input (1/4" jack)
- 2 Mic/AUX switchable (1/4" jack/stereo phono)
- Priority inputs, telephone, Mic 1
- Bass/treble control
- 100v/70v loudspeaker output
- 8Ω/4Ω Low Z output option
- Optional 19" rack kit (BKT-PA935A)

Specifications	PA935N
Output Power	35W RMS @ 100v/70v 35W RMS 8Ω/4Ω
Inputs	1 x Mic (1/4" jack) 1 x Mic/AUX (1/4" jack) 1 x Mic/AUX ~ Sat (1/4" jack and stereo phono) 1 x Screw terminal (telephone)
Priority	Telephone, Mic 1
Input Sensitivity/ Impedance	Mic 1/2/3 ~ -50dB/600Ω Aux ~ -15dB/10kΩ Sat ~ 0dB/10kΩ Telephone ~ 0.775v/600Ω
Frequency Response (±3dB)	80Hz ~ 15kHz
Power Requirement	230v AC, 50Hz
Dimensions	290(W) x 76(H) x 185(D)mm
Weight	4.4kg



BKT-935A
19" Rack Bracket Option

